



Automatic Switch Mode Battery Charger

Model
SEC-1215A
15 Amps

Design Features

- Switch mode technology is used for high efficiency, light weight and quiet operation
- User selectable AC input voltage – 120 or 230 VAC
- User selectable (by DIP switch) 2 or 3 stage charging to ensure rapid and safe charging of all types of lead acid batteries – Flooded, AGM, Gel Cell or batteries with an external load
- Fully automatic operation
- Can charge 3 banks of batteries simultaneously, no isolator necessary
- Ammeter and LED power status indicator
- Ideal for charging all types of 12 volt lead-acid batteries
- Protections: short circuit, over current, reverse battery connection

2 YEAR WARRANTY

MODEL NO.	SEC-1215A
PRE-SET INPUT VOLTAGE	120 VAC, 60 Hz
USER SELECTABLE INPUT VOLTAGE	230 VAC, 50 Hz
INPUT FREQUENCY	50 - 60 Hz
OUTPUT VOLTAGE-BOOST DIP SWITCH SELECTABLE	14 VDC, or 14.4 VDC or disabled
OUTPUT VOLTAGE-FLOAT	13.5 VDC
OUTPUT AMPS	15 A
OPERATING TEMPERATURE RANGE	0 - 40° C
WEIGHT, LBS	4.8
WEIGHT, KG	2.2
DIMENSIONS, INCHES (L x W x H)	8.5 x 8.4 x 3.3
DIMENSIONS, MM (L x W x H)	215 x 214 x 82
PROTECTIONS	Short circuit, over current, reverse battery connection
OUTPUT BANKS	3

NOTE: Specifications are subject to change without notice